



ALIZE 6000 E

PORTABLE POWER

Generating Sets Range PRESTIGE

PRODUCT ADVANTAGES

- Large Autonomy
- Electric starter with batteries without maintenance
- HONDA Professional Engine
- Very Silent
- Easy movement thanks to the standard wheels

With its extremely low noise level, electric starting and a full socket panel, this genset offers exceptional EASE OF USE.

Range PRESTIGE

Top of the range equipment that is efficient and with low noise emissions, for a wide range of standard requirements.



This product meets the Qualigen charter, which aims to ensure a high level of quality and guarantee the safety of users. Qualigen: commitment to safety and quality.

ALIZE 6000 E

GENERAL SPECIFICATIONS

Range	PRESTIGE
Frequency (Hz)	50
Max power LTP (kW) *	5.60
Nominal voltage (V)	230
Number of Phase	Single phase
Fuel	Petrol
Tank (L)	24
75% cons. (l/h) *	2.50
75% Autonomy (h) *	9.60
Sound power level guaranteed LwA dB(A)	93
Acoustic pressure level @1m in dB(A)	78.18210611482180
Acoustic pressure level @7m in dB(A)	64.07168175646740

ENGINE SPECIFICATIONS

Engine brand	HONDA
Engine type	GX390E
Distribution	O.H.V.
Start	Electrical
Low Oil pressure shutdown	Oui
Displacement (cm ³)	389
Oil capacity (L)	1.10

ALTERNATOR SPECIFICATIONS

Technology	Without collar or brush
AVR Regulation	No
Indication of protection	IP 23
Insulation class	H

PLUGS AND PANEL DESCRIPTIVE

2 230V 10/16A sockets - circuit breaker + 1 230V 32A socket - circuit breaker + hour meter

DIMENSIONS AND WEIGHT

Length (cm)	78
Width (cm)	59
Height (cm)	75.50
Dry Weight (kgs)	130

PACKAGING

Packaging type	Box / Pallet
Length (cm)	80
Width (cm)	61
Height (cm)	89.50
Weight (kg)	147.50
Pallet type	
Number of box by pallet	0
Pallet height (cm)	0
weight of the packaged Pallet (kg)	0



ACCESSORIES SUPPLIED



User and maintenance manual

OPTIONS



R02B	R02B	This set includes a differential switch, a hour meter, the plugs and a thermal circuit breaker.
R05M	R05M	The manual changeover switch is used to connect and disconnect a generating set manually to a domestic circuit when there is a power cut.
RBH1	RBH1	Box of 24 o.5L cans of oil or 20 1 L cans of oil (SAE 15W40)
RBH0-5	RBH0-5	Box of 24 0.5L cans of oil or 20 1 L cans of oil (SAE 15W40).
RPM	RPM	Male plugs for all models made up of : 2 x 16 A/230 V, EEC17: 1 x 16A/230 V, 1 x 32A/230 V and 1 x 16A/400V
RPQ	RPQ	For earthing your generator set. Galvanised 1 m long spike, supplied with 2 m of 10 mm ² cable.