



DIESEL 6000 E XL C

PORTABLE POWER

Generating Sets Range DIESEL

PRODUCT ADVANTAGES

- Entire group guaranteed 3 years
- KOHLER air-cooled industrial engine
- Large Autonomy
- Comfort of prehension thanks to the ergonomic handles
- Electric starter with batteries without maintenance

OIL SAFETY Thanks to this functionality, the engine will not start or will stop during its functioning if the oil level for gasolines or the oil pression for diesels is to low : your generating set is perfectly protected !

Range DIESEL

Both long run times and very long life for professional applications.



DIESEL 6000 E XL C

GENERAL SPECIFICATIONS

Range	DIESEL
Frequency (Hz)	50
Max power LTP (kW) *	5.20
Nominal voltage (V)	230
Number of Phase	Single phase
Fuel	Fuel
Tank (L)	16
75% cons. (l/h) *	1.20
75% Autonomy (h) *	13.30
Sound power level guaranteed LwA dB(A)	108
Acoustic pressure level @1m in dB(A)	93.15462905419090
Acoustic pressure level @7m in dB(A)	78.795881787498

ENGINE SPECIFICATIONS

Engine brand	KOHLER DIESEL
Engine type	KD440E
Distribution	Diesel O.H.V.
Start	Electrical
Low Oil pressure shutdown	Oui
Displacement (cm ³)	442
Oil capacity (L)	1.50

ALTERNATOR SPECIFICATIONS

Technology	Without collar or brush
AVR Regulation	No
Indication of protection	IP 23
Insulation class	H

PLUGS AND PANEL DESCRIPTIVE

1 230V 10/16A socket - circuit breaker + 1 230V 32A socket- circuit breaker

DIMENSIONS AND WEIGHT

Length (cm)	81
Width (cm)	55.50
Height (cm)	59
Dry Weight (kgs)	103

PACKAGING

Packaging type	Box
Length (cm)	82
Width (cm)	56.50
Height (cm)	60
Weight (kg)	106
Pallet type	120/80
Number of box by pallet	6
Pallet height (cm)	193
weight of the packaged Pallet (kg)	646



ACCESSORIES SUPPLIED



User and maintenance manual



Floor maintaining slot



Ergonomic handle grip



Battery without maintenance

OPTIONS



R02

R02

This set includes the hour meter and the differential circuit breaker.



R05M

R05M

The manual changeover switch is used to connect and disconnect a generating set manually to a domestic circuit when there is a power cut.

34992310
02575

RKB1HD

ERR: not found in dict valeurs

no picture

34992310
01745

RKDS1

Maintenance kit for KOHLER CH350E and CH440E engines (Diesel 6000 E XL C - Diesel 6500 TE XL C).



RH1

RH1

Cover for SDMO's generating sets, welding sets and water pumps



RPM

RPM

Male plugs for all models made up of : 2 x 16 A/230 V, EEC17: 1 x 16A/230 V, 1 x 32A/230 V and 1 x 16A/400V



RPQ

RPQ

For earthing your generator set. Galvanised 1 m long spike, supplied with 2 m of 10 mm² cable.



RBAC

RBAC

Removable storage box