



HX 3000

PORTABLE POWER

Generating Sets Range INTENS

PRODUCT ADVANTAGES

- Entire group guaranteed 3 years
- HONDA Professional Engine
- Solid and high-performance equipment

Range INTENS

Equipment that is robust, long-lasting and simple to use for repetitive operations in difficult conditions.



This product meets the Qualigen charter, which aims to ensure a high level of quality and guarantee the safety of users. Qualigen: commitment to safety and quality.

HX 3000

GENERAL SPECIFICATIONS

Range	INTENS
Frequency (Hz)	50
Max power LTP (kW) *	3
Nominal voltage (V)	230
Number of Phase	Single phase
Fuel	Petrol
Tank (L)	3.10
75% cons. (l/h) *	1.30
75% Autonomy (h) *	2.40
Sound power level guaranteed LwA dB(A)	95
Acoustic pressure level @1m in dB(A)	81.04636103655170
Acoustic pressure level @7m in dB(A)	66.15022514670210

ENGINE SPECIFICATIONS

Engine brand	HONDA
Engine type	GX200
Distribution	O.H.V.
Start	Starter
Low Oil pressure shutdown	Oui
Displacement (cm ³)	196
Oil capacity (L)	0.60

ALTERNATOR SPECIFICATIONS

Technology	Without collar or brush
AVR Regulation	No
Indication of protection	IP 23
Insulation class	H

PLUGS AND PANEL DESCRIPTIVE

2 230V 10/16A sockets - circuit breaker

DIMENSIONS AND WEIGHT

Length (cm)	59
Width (cm)	46
Height (cm)	43
Dry Weight (kgs)	41

PACKAGING

Packaging type	Box
Length (cm)	60.50
Width (cm)	46
Height (cm)	44
Weight (kg)	43
Pallet type	140/110
Number of box by pallet	15
Pallet height (cm)	145
weight of the packaged Pallet (kg)	661



3/15/2016

HX 3000 - PORTABLE POWER - Generating Sets INTENS

This document is not contractual - The SDMO company reserves the right to modify any of the characteristics stated in this document without notice, in a constant effort to improve the quality of its products. *ISO 8528.

SDMO Industries - 12bis, rue de la Villeneuve - CS 92848 - 29228 BREST CEDEX 2 - France - Tel +33(0)2 98 41 41 41 - Fax +33 (0)2 98 41 63 07 - www.sdmo.com

ACCESSORIES SUPPLIED



Funnel



User and maintenance manual

OPTIONS



R01

R01

This set includes the hour meter and the differential circuit breaker.



R05M

R05M

The manual changeover switch is used to connect and disconnect a generating set manually to a domestic circuit when there is a power cut.



R06

R06

Trolley kit for 2 and 3 kW generating sets.



34992310
33104

**ERR: not found in dict
valeurs**

Maintenance kit for Honda GX160 and GX200 engine (except Alizé 3000)



RBH1

RBH1

Box of 24 0.5L cans of oil or 20 1 L cans of oil (SAE 15W40)



RBH0-5

RBH0-5

Box of 24 0.5L cans of oil or 20 1 L cans of oil (SAE 15W40).



RHO

RHO

Cover for SDMO 's generating sets, welding sets and water pumps



RPM

RPM

Male plugs for all models made up of : 2 x 16 A/230 V, EEC17: 1 x 16A/230 V, 1 x 32A/230 V and 1 x 16A/400V



RPQ

RPQ

For earthing your generator set. Galvanised 1 m long spike, supplied with 2 m of 10 mm² cable.



RKD1

RKD1

kit of two diferential removable adapters for domestic sockets. Schema for ground bonding with isolated neutral