



## HX 4000

PORTABLE POWER

Generating Sets Range INTENS

### PRODUCT ADVANTAGES

- Entire group guaranteed 3 years
- HONDA Professional Engine
- Solid and high-performance equipment

### Range INTENS

Equipment that is robust, long-lasting and simple to use for repetitive operations in difficult conditions.



This product meets the Qualigen charter, which aims to ensure a high level of quality and guarantee the safety of users. Qualigen: commitment to safety and quality.

## HX 4000

### GENERAL SPECIFICATIONS

Range	INTENS
Frequency (Hz)	50
Max power LTP (kW) *	4
Nominal voltage (V)	230
Number of Phase	Single phase
Fuel	Petrol
Tank (L)	5.30
75% cons. (l/h) *	2.10
75% Autonomy (h) *	2.50
Sound power level guaranteed LwA dB(A)	95
Acoustic pressure level @1m in dB(A)	81.08460754438680
Acoustic pressure level @7m in dB(A)	66.50029060734620

### ENGINE SPECIFICATIONS

Engine brand	HONDA
Engine type	GX270
Distribution	O.H.V.
Start	Starter
Low Oil pressure shutdown	Oui
Displacement (cm <sup>3</sup> )	270
Oil capacity (L)	1.10

### ALTERNATOR SPECIFICATIONS

Technology	Without collar or brush
AVR Regulation	No
Indication of protection	IP 23
Insulation class	H

### PLUGS AND PANEL DESCRIPTIVE

2 230V 10/16A sockets - circuit breaker

### DIMENSIONS AND WEIGHT

Length (cm)	71.50
Width (cm)	57
Height (cm)	49
Dry Weight (kgs)	56

### PACKAGING

Packaging type	Box
Length (cm)	73
Width (cm)	58
Height (cm)	49.50
Weight (kg)	58.50
Pallet type	120/80
Number of box by pallet	6
Pallet height (cm)	161.50
weight of the packaged Pallet (kg)	361



## ACCESSORIES SUPPLIED



Funnel



User and maintenance manual

## OPTIONS



R01

**R01**

This set includes the hour meter and the differential circuit breaker.



R05M

**R05M**

The manual changeover switch is used to connect and disconnect a generating set manually to a domestic circuit when there is a power cut.



RKB2

**RKB2**

Trolley kit for the generating sets superior to 6kW



34992310  
01585

**R33**

Maintenance kit for Honda GX270



RH1

**RH1**

Cover for SDMO 's generating sets, welding sets and water pumps



RPM

**RPM**

Male plugs for all models made up of : 2 x 16 A/230 V, EEC17: 1 x 16A/230 V, 1 x 32A/230 V and 1 x 16A/400V



RPQ

**RPQ**

For earthing your generator set. Galvanised 1 m long spike, supplied with 2 m of 10 mm<sup>2</sup> cable.



RKD1

**RKD1**

kit of two diferential removable adapters for domestic sockets. Schema for ground bonding with isolated neutral