



HX 6000 C

PORTABLE POWER

Generating Sets Range INTENS

PRODUCT ADVANTAGES

- Entire group guaranteed 3 years
- HONDA Professional Engine
- Solid and high-performance equipment

Range INTENS

Equipment that is robust, long-lasting and simple to use for repetitive operations in difficult conditions.



HX 6000 C

GENERAL SPECIFICATIONS

Range	INTENS
Frequency (Hz)	50
Max power LTP (kW) *	6
Nominal voltage (V)	230
Number of Phase	Single phase
Fuel	Petrol
Tank (L)	6.10
75% cons. (l/h) *	2.50
75% Autonomy (h) *	2.40
Sound power level guaranteed LwA dB(A)	100
Acoustic pressure level @1m in dB(A)	86.02717842803190
Acoustic pressure level @7m in dB(A)	71.60151590981260

ENGINE SPECIFICATIONS

Engine brand	HONDA
Engine type	GX390
Distribution	O.H.V.
Start	Starter
Low Oil pressure shutdown	Oui
Displacement (cm ³)	389
Oil capacity (L)	1.10

ALTERNATOR SPECIFICATIONS

Technology	Without collar or brush
AVR Regulation	No
Indication of protection	IP 23
Insulation class	H

PLUGS AND PANEL DESCRIPTIVE

1 230V 10/16A socket - circuit breaker + 1 230V 32A socket- circuit breaker

DIMENSIONS AND WEIGHT

Length (cm)	71.50
Width (cm)	57
Height (cm)	59
Dry Weight (kgs)	75

PACKAGING

Packaging type	Box
Length (cm)	73
Width (cm)	58
Height (cm)	59.50
Weight (kg)	77.50
Pallet type	120/80
Number of box by pallet	6
Pallet height (cm)	191.50
weight of the packaged Pallet (kg)	475



ACCESSORIES SUPPLIED



Funnel



User and maintenance manual

OPTIONS



R02

R02

This set includes the hour meter and the differential circuit breaker.

R05M

R05M

The manual changeover switch is used to connect and disconnect a generating set manually to a domestic circuit when there is a power cut.

RKB2

RKB2

Trolley kit for the generating sets superior to 6kW

RH1

RH1

Cover for SDMO 's generating sets, welding sets and water pumps

RPM

RPM

Male plugs for all models made up of : 2 x 16 A/230 V, EEC17: 1 x 16A/230 V, 1 x 32A/230 V and 1 x 16A/400V

RPQ

RPQ

For earthing your generator set. Galvanised 1 m long spike, supplied with 2 m of 10 mm² cable.