

# Generating Sets PHOENIX 2800



## GENERAL SPECIFICATIONS

Max power LTP (kW) *	3
Nominal voltage (V)	230
Number of Phase	Single phase
Fuel	Petrol
Tank (L)	4.10
75% Autonomy (h) *	3.20
Sound power level guaranteed LwA dB(A)	96
Acoustic pressure level @7m in dB(A)	67.53022514670210

## ENGINE SPECIFICATIONS

Engine brand	KOHLER
Start	Starter
Displacement (cm <sup>3</sup> )	208
Oil capacity (L)	0.60

## ALTERNATOR SPECIFICATIONS

Indication of protection	IP 23
Insulation class	H

## PRODUCT ADVANTAGES

- Good value for money
- Entire group guaranteed 2 years or 1000 hours
- Made in France

## Range PHOENIX

Ease the gardening and DIY far from electric sockets.



## PLUGS AND PANEL DESCRIPTIVE

2 230V 10/16A sockets - circuit breaker

## DIMENSIONS AND WEIGHT

Length (cm)	59
Width (cm)	46
Height (cm)	43
Dry Weight (kgs)	42

This product meets the Qualigen charter, which aims to ensure a high level of quality and guarantee the safety of users. Qualigen: commitment to safety and quality.

## OPTIONS

- RKBP1
- R30
- RHO



Can I use my generator :

